


# 3XLOGIC



## VISIX VX-6M-360-IA-02 360 Fisheye Outdoor Vandal Dome Camera

### Quick Start Guide

Ver. 1.0 / 2020.03

Before installing and using the camera, please read this manual carefully.

Be sure to keep it handy for future reference.



a. This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:  
1. This device may not cause harmful interference.  
2. This device must accept any interference received, including interference that may cause undesired operation.  
Note: This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this equipment in a residential area is likely to cause harmful interference in which case the user will be required to correct the interference at his own expense.

b. This device complies with CAN ICES-3 (A)/NMB-3(A)  
c. This device is UL and ULC E467574 (Safety) certified.  
d. This device complies with CE 2014/30/EU – EMC Directive, 2015/863/EU RoHS3 as part of 2011/65/EU RoHS  
e. This device complies with WEEE

## Safety Information

**CAUTION**  
**RISK OF ELECTRIC SHOCK.**  
**DO NOT OPEN**

CAUTION:  
TO REDUCE THE RISK OF ELECTRIC SHOCK, DO NOT REMOVE COVER (OR BACK) NO USER SERVICEABLE PARTS INSIDE. REFER SERVICING TO QUALIFIED SERVICE PERSONNEL.

This symbol indicates that dangerous voltage consisting a risk of electric shock is present within this unit.

This exclamation point symbol is intended to alert the user to the presence of important operating and maintenance (servicing) instructions in the literature accompanying the appliance.

### WARNING

To prevent damage which may result in fire or electric shock hazard, do not expose this appliance to rain or moisture.

### WARNING

- Be sure to use only the standard adapter that is specified in the specification sheet. Using any other adapter could cause fire, electrical shock, or damage to the product.
- Incorrectly connecting the power supply or replacing battery may cause explosion, fire, electric shock, or damage to the product.
- Do not connect multiple cameras to a single adapter. Exceeding the capacity may cause abnormal heat generation or fire.
- Securely plug the power cord into the power receptacle. Insecure connection may cause fire.
- When installing the camera, fasten it securely and firmly. A falling camera may cause personal injury.
- Do not place conductive objects (e.g. screw drivers, coins, metal things, etc.) or containers filled with water on top of the camera. Doing so may cause personal injury due to fire, electric shock, or falling objects.

- Do not install the unit in humid, dusty, or sooty locations. Doing so may cause fire or electric shock.
- If any unusual smells or smoke come from the unit, stop using the product. In such case, immediately disconnect the power source and contact the service center. Continued use in such a condition may cause fire or electric shock.
- If this product fails to operate normally, contact the nearest service center. Never disassemble or modify this product in any way.
- When cleaning, do not spray water directly onto parts of the product. Doing so may cause fire or electric shock.

### CAUTION

- Do not drop objects on the product or apply strong shock to it. Keep away from a location subject to excessive vibration or magnetic interference.
- Do not install in a location subject to high temperature low temperature or high humidity. Doing so may cause fire or electric shock.
- If you want to relocate the already installed product, be sure to turn off the power and then move or reinstall it.
- Remove the power plug from the outlet when there is a lightning. Neglecting to do so may cause fire or damage to the product.
- Keep out of direct sunlight and heat radiation sources. It may cause fire.
- Install it in a place with good ventilation.
- Avoid aiming the camera directly towards extremely bright objects such as sun, as this may damage the image sensor.
- Apparatus shall not be exposed to dripping or splashing and no objects filled with liquids, such as vases, shall be placed on the apparatus.
- The Mains plug is used as a disconnect device and shall stay readily operable at any time.


## Important Safety Instructions

### WARNING


- Read these instructions.
- Keep these instructions.
- Heed all warnings.
- Follow all instructions.
- Do not use this apparatus near water.
- Clean only with dry cloth.
- Do not block any ventilation openings. Install in accordance with the manufacturer's instructions.
- Do not install near any heat sources such as radiators, heat registers, or other apparatus (including amplifiers) that produce heat.
- Do not defeat the safety purpose of the polarized or grounding-type plug. A polarized plug has two blades with one wider than the other. A grounding type plug has two blades and a third grounding prong. The wide blade or the third prong is provided for your safety. If the provided plug does not fit into your outlet, consult an electrician for replacement of the obsolete outlet.
- Protect the power cord from being walked on or pinched particularly at plugs, convenience receptacles, and the point where they exit from the apparatus.
- Only use attachments/accessories specified by the manufacturer.
- Use only with cart, stand, tripod, bracket, or table specified by the manufacturer, or sold with the apparatus.
- Unplug this apparatus when a cart is used. Use caution when moving the cart/apparatus combination to avoid injury from tip-over.
- Refer all servicing to qualified service personnel. Servicing is required when the apparatus has been damaged in any way, such as power supply cord or plug is damaged, liquid has been spilled or objects have fallen into the apparatus, the apparatus has been exposed to rain or moisture, does not operate normally, or has been dropped.



## Step 1. Product & Accessories




## Step 2. Part Name



## Step 3. Disassemble the Camera

Before installing your camera, please review the following cautionary items:

- You have to confirm whether the install location can bear five times of the weight of your camera.
- Do not let the cable be caught in improper positions or the electric line cover to be damaged. This may cause a breakdown or fire.
- When installing your camera, do not allow any person to approach the installation site. If you have any valuable underneath the install location, move them.



**1** Detach the dome cover from bottom case using the supplied torx before installing the camera

**⊠** The camera includes a sensor at the camera's module. For the sensor to function properly, the camera's dome includes a special hole the sensor.


**⊠** When assembling the camera, please make sure the sensor hole on the camera's dome is positioned on top of the corresponding sensor on the camera.

**⊠** Be sure to assemble the dome cover and bottom case to match the case outline.

**⊠ Reset to the Factory Default**  
Press the reset button for 5 seconds to return the setup to the factory default.


**⊠ Warning:**  
If you press the 'Reset' button, you will lose all settings data. If needed, please, make a note of all necessary settings before resetting.

## Step 4. Installation




- Detach the camera's cover dome from the camera module by unscrewing the three cover dome screws using the supplied torx.
- Use the camera or mounting template to mark and drill necessary holes in the wall or ceiling.
- Pull wires through and make connections.
  - ⊠ How to connect to the network through the water proof cable**  
Put the Lan cable into (a), then (b) will be assembled to (a) tightly. As a final step, (c) need to be assembled to (b) without making any space.
- Using two(2) included screws, mount and secure the camera to the mounting surface.
- Affix the over dome to the camera base to complete the installation.
- Detach the protection film from the dome cover.

## Step 5. Installation Using Mount Plate



- 1 Detach the cover dome from the camera module by unscrewing the three cover dome screws.
- 2 Using the metal mount plate, mark and drill the necessary holes in the wall or ceiling.
- 3 Pull wires through and make connections.
- 4 Using the three (3) included screws, mount and secure the camera to the wall or ceiling.
- 5 Attach the camera base to the metal mount by snapping it into the place using the two metal handles.
- 6 Secure the cover dome onto the camera base to complete the installation.
- 7 Detach the protection film from the dome cover.

## Step 6. Installation Using Mount Bolt and Nut



- 1 Using the template sheet, mark and drill the cabling holes on the wall/ceiling.
- 2 Secure the two long mounting screws to the camera's base.
- 3 Pass the wires through the mount bracket and make all necessary connections.
- 4 Mount the camera to the mounting surface by using the 2 mounting nuts. Rotate the locking discs over the screws until the camera is held tightly from the mounting surface.
- 5 Secure the cover dome onto the camera base to complete the installation.
- 6 Detach the protective film from the dome cover.

## Step 7. Cabling

### Two Options

Use a PoE-enabled switch to connect data and power through a single cable and begin viewing and recording images instantly. A non-PoE switch will require an adaptor for power transmission.



#### 1. Using a PoE-Enabled Switch

The Camera is PoE-compliant, allowing transmission of power and data via a single Ethernet cable. PoE eliminates the need for the different cables used to power, record, or control the camera. Follow the illustration below to connect the camera to a PoE-enabled switch using an Ethernet cable.



#### 2. Using a Non-PoE Switch

If a PoE-enabled switch is not used, use a power adaptor for power transmission and non-PoE switch for data transmission. Follow the illustrations below to connect the camera without a PoE-enabled Switch.



#### 1 Power Connection

Please, check the voltage and current capacity of rated power carefully.

Rated Power	Power Consumption	PoE
DC 12V	7.5W	IEEE 802.3af Class3

#### 2 Network Connection

#### 3 Audio In

Connect the 'Audio In' cable of the camera to a device (microphone, etc...).

#### 4 Audio Out

Connect the 'Audio Out' cable of the camera to device (speaker, etc...).

Audio Out supports only RTSP Back channel function. It plans to make it available on the web later.


#### 5 Alarm Out

Connects to the alarm lights, siren or lamps. Sensor types are normal open and normal close. The c of the alarm output device should connect to DO1(N.O.) and DO1 COM of the cable slot.

#### 6 Alarm In

The cable of the sensor/alarm input device should connect to Yellow and White line of the Alarm cable.

## Step 8. IP Installer



### 6 Select the network type.

The default network type of the camera is DHCP mode.

If you have a DHCP server, it will automatically set the Camera IP.

If you do not have a DHCP server, Camera IP is set to 192.168.1.80 after one minute.

Input IP settings information when the network type is set to STATIC. Always click **Save** after changing IP Settings.

Default TCP/IP information  
 - IP: 192.168.1.80  
 - Subnet Mask: 255.255.255.0  
 - Gateway: 192.168.1.1  
 - DNS : 168.126.63.1

Change the port as necessary when the network type is set to STATIC.

A 'Port Forwarding' has to be set for external access to the camera.

Refer to the manual of the network hub for 'Port Forwarding' settings.

An additional change of HTTPS, RTSP port can be done at Web Viewer > Admin page.

Change Password.

Default ID / PW : admin / admin

The default user ID and password must be changed for security reasons. Video will not stream from the camera until the default admin password is changed. Enter the default credentials (admin / admin) and click **Change Password**. Enter and confirm a unique password, and click **OK** to complete the change.

The ID and PW will be set to default value when a 'factory reset' is performed on the camera.

Make sure to click the **Save** button to save changed values.


An **Apply** message will deploy when the settings are applied normally, or an error message will deploy if the settings fail to apply. This step saves settings to the camera itself.

After applying the new camera settings, click **Save to VIGIL**. This step saves the camera to the VIGIL Server software. The camera will occupy the camera channel you selected in Step 1 (iv) of this section.

Rebooting or Resetting the Camera to Factory Settings  
 If a factory reset is required, login to the camera's browser interface (enter IP into a browser URL bar and login to the camera) then navigate to **Setup > System > Factory Reset**. To perform a basic camera retart, Navigate to **Setup > System > Restart**

## Step 9. Viewing / Dewarping Video in VIGIL Client

After adding the camera to VIGIL Server, 3xLOGIC recommends VIGIL Client for viewing live and playback. Client's powerful tool set can be leveraged by users to thoroughly and quickly review camera footage and other data collected by a VIGIL Server. After adding a VIGIL Server to VIGIL Client, refer to the steps in this section for details on viewing the camera's footage in VIGIL Server.



After launching VIGIL Client, extend the **Servers** node located in the Sites tab treeview then double-click the desired VIGIL Server to reveal available devices and tools.

Expand the **Camera** node to reveal the VIGIL Server's cameras.

Double-click the desired camera. The camera's live stream will be automatically displayed in the viewing area.


Live Edge Controls instantly grant the user access to common tools such as Capture Still Image, Instant Replay and Stream Type Selection

Stream information such as FPS rate, bitrate and CODEC type are listed when the cursor hovers over the bottom edge of the frame.

To dewarp the camera footage into quadrants, right-click in the viewer and select **360 Dewarping > 360 View and Source Video**.

Note: 360 Dewarping must be selected as the camera's **Camera Control Type** in VIGIL Server camera setup settings. A VIGIL 360 Dewarping license is also required. Video can also be exported with VIGIL DV Player which allows dewarping and digital PTZ control of 360 camera video.

Select Instant Replay from the Live Edge Controls to open the last 5 minutes of footage from the camera or perform a playback search to review a custom time range of playback. A Playback viewer featuring the requested footage will deploy.



For further details on reviewing and exporting playback and other advanced features such as audio recording and two-way audio talk, POS Data OSD and more, please visit [www.3xlogic.com](http://www.3xlogic.com) and consult the product documentation library for VIGIL Client-related support documentation.

## Disposal of Old Appliance



1. When this crossed-out wheel bin symbol is attached to a product it means the product is covered by the European Directive 2002/96/EC.
2. All electrical and electronic products should be disposed of separately from the municipal waste stream in accordance to laws designated by the government or the local authorities.
3. The correct disposal of your old appliance will help prevent potential negative consequences for the environment and human health.
4. For more detailed information about disposal of your old appliance, please contact your city office, waste disposal service or the shop where you purchased the product.